

EVGA<sup>®</sup> SUPERNOVA

1000 P2



1000W PLATINUM POWER SUPPLY

**Table of contents**

<b>Introduction</b> .....	3
<b>Safety Information</b> .....	3
<b>Features</b> .....	4
<b>Installation</b> .....	4
<b>SuperNOVA 1000 P2 Cable Configuration</b> .....	6
<b>SuperNOVA 1000 P2 Specification</b> .....	6

**Introduction: Premium Power**

Thank you for purchasing an EVGA SuperNOVA PLATINUM series power supply. The SuperNOVA PLATINUM series are premium quality power supplies intended to meet the needs of the most demanding PC enthusiast systems. Designed with enthusiast needs in mind the SuperNOVA PLATINUM series is the best choice to power next generation systems.


**SuperNOVA 1000W PLATINUM**
**Safety Information**

**WARNING:** This unit has no user-serviceable parts inside. Opening the casing presents a risk of electrocution and will void the warranty. EVGA will not be responsible for any result of improper use, use for which the product was not intended, or use inconsistent with the warranty terms (available for review at [www.evga.com/support/warranty/](http://www.evga.com/support/warranty/)) and this manual (also available at [www.evga.com/support/manuals/](http://www.evga.com/support/manuals/)).

## Features

### STABLE POWER

The SuperNOVA PLATINUM series has outstanding electrical performance with **ultra stable voltage** and extremely **clean outputs**. This can help you achieve the highest possible overclock, or just the most stability and reliability. The SuperNOVA PLATINUM series also has high efficiency **up to 90%** and is **80PLUS PLATINUM** certified.

### THE BEST PROTECTION

The SuperNOVA PLATINUM series comes equipped with the most comprehensive protection set possible, including Over Voltage Protection (**OVP**), Under Voltage Protection (**UVP**), Over Power Protection (**OPP**), Short Circuit Protection (**SCP**), and Over Current Protection (**OCP**). This product is also covered by an exceptional **10-year warranty** and EVGA's legendary customer service and support.

### SUPERIOR BUILD QUALITY

The SuperNOVA PLATINUM series is built to the highest standards, using **Japanese capacitors** rated at 105 degrees Celsius and high quality brand-name semiconductor components for the highest performance and reliability.


### MODULAR DESIGN

The SuperNOVA PLATINUM series is designed with the enthusiast in mind, with fully modular cables to maximize airflow and keep your system looking slick and clean.


## Installation

1. Remove the power supply from its packaging.


2. Use the screws provided with your case to install the power supply into your computer. **NOTE:** It is recommended to install the power supply with the fan facing down. However, if your case places the power supply at the bottom of the case and there are no ventilation holes there, it may be best to install the power supply with the fan facing up for greater efficiency and reliability.



3. Connect the 24-pin ATX cable to the motherboard.




4. Connect the 8-pin EPS12V cable to the motherboard.




5. Connect the 6/8-pin PCIe cables to your graphics card(s). **NOTE:** Do not attempt to plug an 8-pin PCIe cable into a 6-pin connector without first detaching the two extra pins.




6. Connect the SATA cables to your power supply and drives (hard drives, solid state drives, optical drives).



7. Connect the peripheral "molex" connectors to the power supply and your fans and other devices.



8. Connect the AC power cord to your power supply and to the wall, and turn the power switch to the ON position.



## SuperNOVA 1000 P2 Cable Configuration

Modular Connector	Cables	Cable Color
MB	1x ATX 24 pin	Black
CPU1	2x EPS12V 4+4 pin	Black
CPU2		
VGA1	4x PCIe 6+2 pin	Red
VGA2		
VGA3		
VGA4		
VGA5		
VGA6	2x PCIe 6+2 pin + 6 pin	
SATA1	2x SATA 5 pin x3	Black
SATA2		
SATA3		
SATA4	2x SATA 5 pin x2	
PERP1	1x Molex 4 pin x3	Black
PERP2	1x Molex 4 pin x2 + 1 Floppy	Black

## SuperNOVA 1000 P2 Specifications

EVGA	SuperNOVA 1000W PLATINUM				+50°C ambient @ full load	
AC Input	100-240 VAC 15A, 60 / 50 Hz					
DC Output	+5V	+3.3V	+12V	-12V	+5Vsb	
MAX output, A	20	20	83.3	0.5	2.5	
Combined, W	100		999.6	6.0	12.5	
Output power, Pcont	1000W @ +50°C					



Dimensions: 85mm (H) x 150mm (W) x 200mm (L)

**Over Voltage Protection, Under Voltage Protection, Short Circuit Protection, Over Power Protection, Over Current Protection.**

# EVGA. SUPERNOVA

EVGA Corp. 2900 Saturn Street, Suite B Brea, CA 92821

[www.evga.com](http://www.evga.com)